

Communication Register Map for iM 1000



No	Parameter	Data Type	Address
1	Watts Total	float	40101
2	Watts R phase	float	40103
3	Watts Y phase	float	40105
4	Watts B phase	float	40107
5	PF average (Instantaneous)	float	40109
6	PF R phase	float	40117
7	PF Y phase	float	40119
8	PF B phase	float	40121
9	VLL average	float	40133
10	Vry phase	float	40135
11	Vyb phase	float	40137
12	Vbr phase	float	40139
13	VLN average	float	40141
14	V R phase	float	40143
15	V Y phase	float	40145
16	V B phase	float	40147
17	Current Total	float	40149
18	Current R phase	float	40151
19	Current Y phase	float	40153
20	Current B phase	float	40155
21	Frequency	float	40157
22	Wh received	float	40159